

## features

- True RMS measurement
- Low set & High set
- Operation hour recording
- Fault & Trip LED Indication
- Trip value recording (3 memory)
- Total trip count information
- Programmable relay output
- Programmable software lock
- Selectable frequency (50 / 60 Hz)
- Auto Z.C.T. connection check (open / short)
- 35 mm wide DIN Rail mount

## Technical Specification

Technical data / Setting range

### TECHNICAL DATA


Measurement	True RMS Ampere
Power supply	240 V AC (± 10%)
Rated frequency	50 / 60 Hz
Output relay / Alarm	5A / 240 V AC
Tripping contact	SPDT 5A / 240 V AC
Weight	~320 g
Operating temp.	0°C ~ +55°C
Standard	IEC : 61000-4-2/ 4-4 / 4-5 / 255-5:1

### SETTING RANGE

Current setting $I_{\Delta n} > (A)$	0.03 ~ 30.0 Ampere
Trip time setting $t > (sec)$	0.05 ~ 20.0 (0.1 sec. step)
High-set $I_{\Delta n} \gg (A)$	OFF or 5 ~ 50 Ampere (5 Amp. step)
High-set trip time	Fixed at 30ms

## Casing Dimension


35 mm wide DIN Rail mount



All measurement in millimeters

## Panel Description

Overview / Button Functions




## Parameter Modes

Modes definition

SETTING	mode	description
1	$I_{\Delta n} > (A)$	To set leakage current
2	$t > (sec)$	To set trip time
3	$I_{\Delta n} \gg (A)$	To set high set leakage current
<b>INFO</b>		
9	Operation hr.	Device operated in hours (x 1000 hr.)
A	Trip mem.1	Most recent trip value
B	Trip mem.2	Trip value before ( Trip mem.1 )
C	Trip mem.3	Trip value before ( Trip mem.2 )
D	Total trip count	Total number of trips
<b>SPECIAL SETTING MODE</b>		
L	Software lock	Keypad lock : ON or OFF
R1	TripRelay K1 response type	Latching or Non-latching
R2	Output relay K2 function	Programmable relay output
R3	TripRelay K2 response type	Latching or Non-latching
F	Network frequency	Selectable as : 50 Hz or 60 Hz
S	Standby mode	Running LED bar : ON or OFF
Z	Z.C.T. error detection	Automatic detection or OFF

## Wiring Diagram


Wiring connection



## How to do setting

Step by step instruction

When mode display is blank, press **[Select]** button to access to parameter setting mode.



**1** Press **[ Select ]** button while in default mode to access to parameter setting mode:



To scroll thru modes, just press & release the **[Select]** button

**2** Press **[ Up/(+) ]** or **[ Down/(-) ]** button to adjust desire value

For fast increment or decrement, press and hold the UP or Down button

**3** Press **[ Set ]** to store new value and proceed to the next mode.

Press **[ Cancel ]** button to exit mode or undo changes,

All modes exit automatically if left untouched for more than 20 secs.

## Setting Parameters

Modes 1 2 3

### 1 |an > (A) : To set leakage current

- Step 1 :** Press **[ Select ]** once to enter mode **1**.  
Display will show the existing set value. (Range : 0.03 ~ 30.0 Ampere)
- Step 2 :** Set the desired leakage current using the **[ Up / (+) ]** or **[ Down / (-) ]** button. Newly selected value will flash.
- Step 3 :** Press **[ Select ]** to store / confirm new value and advance to mode **2** or press **[ Cancel ]** to undo changes.

### 2 |t > (sec) : To set trip time

- Step 1 :** Press **[ Select ]** until mode **2** is displayed.  
Display will show the existing set value. (Range : 0.05 ~ 20.0 seconds)
- Step 2 :** Set the desired trip time using the **[ Up / (+) ]** or **[ Down / (-) ]** button. Newly selected value will flash.
- Step 3 :** Press **[ Select ]** to store / confirm new value and advance to mode **3** or press **[ Cancel ]** to undo changes.

### 3 |an >> (A) : To set high set leakage current

- Step 1 :** Press **[ Select ]** until mode **3** is displayed.  
Display will show the existing set value. (Range : 5 ~ 50 Ampere or OFF)
- Step 2 :** Set the desired high-set leakage current using the **[ Up / (+) ]** or **[ Down / (-) ]** button. Newly selected value will flash.
- Step 3 :** Press **[ Select ]** to store / confirm new value and advance to mode **2** or press **[ Cancel ]** to undo changes.

## Viewing Info

Modes 9 / A B C / d

### 9 View operation hour x 1000

This mode is not adjustable. For user to view the no. of hour the device in operation.  
Press **[ Select ]** until mode **9** is displayed.  
Display will show the total number of hour device operated. To exit, press **[ Cancel ]**.  
e.g. 0.05 x 1000 = 50 hours

### A B C View trip memory : 3 tripping memories

This mode is not adjustable. For user to view tripped value only.  
Press **[ Select ]** until mode **A** is displayed.  
The display will show the most recent tripped value.  
Press **[ Select ]** again to go to mode **B**, the display will show the tripped value before **A**.  
Press **[ Select ]** again to go to mode **C**, the display will show the tripped value before **B**.  
To exit, press **[ Cancel ]**.

### d View total trip count / To reset total trip count / trip memory

This mode records the total number of tripping that has occurred for the device (maximum = 255). This value cannot be reset by any timer.  
Press **[ Select ]** until mode **d** is displayed.  
Display will show **---** (no tripping has occurred) or a value between 1 to 255.  
To exit, press **[ Cancel ]** button.

## Special Setting Modes

Modes L OFF ON / r1 r2 r3 / F - C

User can lock the keypad on the device to avoid unauthorized or accidental adjustment to the settings and to do special settings.

- When NO mode is selected (mode display is blank).  
i) Press **[ Select ]** and **[ Cancel ]** button simultaneously and hold for 5 seconds.  
ii) Press **[ Up / (+) ]** or **[ Down / (-) ]** button to select or modify  
iii) Press **[ Set ]** button to confirm and proceed to next mode

### L Software keypad lock

**OFF** : Parameters modification : Allowed  
**ON** : Parameters modification : Not Allowed

### r1 Trip relay K1 response type

**Lc** : Latching trip signal  
**nLc** : Non-latching trip signal

### r2 Output relay K2 function

**ALr** : Alarm output (Lc/nLc)  
**dUr** : Device failure output  
**ELs** : Earth leakage start signal output(nLc)  
**ErP** : Tripping output (Lc/nLc)

### r3 K2 response type

**Lc** : Latching trip signal  
**nLc** : Non-latching trip signal  
**nA** : Not Available

### F Electrical network system frequency

Electrical network frequency setting:  
**50** = 50 Hz **60** = 60 Hz

### - Standby option

**OFF** : De-activate **ON** : Activate

A flashing decimal on the mode display indicate standby mode is enable. After about 3 minutes of idle and no leakage is detected, running LED bar will be displayed instead of the real time leakage current. Standby mode automatically exits on leakage detection or when any button is depressed. When device trips, standby mode is temporary de-activated until device is reset. Alternatively, simply press **[Cancel]** button when powering up the device to activate or de-activate standby function.

### C Z.C.T error detection

**Aut** : Automatic check at 2 hour interval  
**OFF** : Disable detection

For manual check, press & hold the **[ Test ]** button for 2 secs. If Z.C.T. connection is open or shorted, then the Z.C.T. error LED will.

After the Ct mode, the display will show **End** <-> **SEt**.

Press **[Set]** to confirm all of the above settings or press **[Cancel]** to go back one previous mode.

Press & hold **[Cancel]** for 3 seconds to exit and abort the modification without saving (previous setting unchanged).

New setting only takes effect when **[Set]** button is pressed during **End** <-> **SEt** is displayed.

## Manual ' test trip '

Test device for fault in tripping

Manual test trip allows the user to test the device for any fault in tripping. To do a manual test trip, follow the instruction below:

When NO mode is selected (mode display is blank).

- i) Press & hold **[ Test ]** button for 5 seconds.  
The mode display decimal will flash 5 times to indicate 5 seconds count.
- ii) Release the button when the display show : **-t**
- iii) Mode starts to count down from 5 and trips at zero. The display will show : **ErP**  
To abort test when mode has not counted down to zero, press the **[ Cancel ]** button.

## Reset Trip Memory

Reset recorded trip memories or total trip count

Press **[ Select ]** button until mode **[A]** is displayed.

If the display show **---** ( NO tripping has occurred ), no resetting is required.

If the display show a certain value ( tripping has occurred ), then follow the steps below:-

Press **[ Cancel ]** button and hold for 3 seconds in current mode -> mode **A** or Press **[ Up ]** and **[ Down ]** button simultaneously and hold for 3 seconds in mode **A**.  
(The mode display decimal will flash 3 times to indicate 3 seconds count)

The display will reset to show **ErP**. To exit, press the **[ Cancel ]** button.

## Z.C.T. Specification

Zero phase current transformer

For optimum performance and accuracy, we recommend that you use only the original Z.C.T. intended for use with the device. Using others Z.C.T. could compromise on the performance or accuracy. The warranty does not cover product failures which have been caused by use of other Z.C.T.

(Type)	83905	83906
Hole Diameter (mm)	50	100
A (mm)	125	183
B (mm)	112	153
C (mm)	35	35
Weight (kg)	~0.70	~1.40
Frequency	50 / 60 Hz	
Current Ratio	200 / 1.5	
Insulation	600V / 50 Hz 1 min.	
Sec. Burden	10 VA	

Contact your supplier for more information.

